



**SET POINT ADJUSTMENT:**  
 THE OUTPUT SET POINT MAY BE ADJUSTED WITH THE REMOTE 1K POTENTIOMETER PROVIDED OR WITH A 0-5 VDC SIGNAL TO THE J3 CONNECTOR ON THE STEPPER DRIVE CONTROL. MAKE CONNECTIONS TO J3-2(+) & J3-3(-). A NOMINAL +5 VDC SETPOINT SUPPLY IS AVAILABLE AT J3-1 (ADJUSTABLE AT TRIMPOT R22).

SPECIFICATIONS									
WIRING	INPUT		OUTPUT				TERMINAL CONNECTIONS		
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		INPUT	OUTPUT
				MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA		
SINGLE PHASE	120	50/60	0-120	15	1.80	20	2.40	2-4	4-3
			0-140	15	2.10	-	-	1-4	4-3

1/4-28 X .50 DEEP THREADS (4) PLACES FOR MOUNTING.

UNLESS OTHERWISE SPECIFIED, TOLERANCE IS # DECIMALS .XX .0008 .06 .002 .XXX .005 HOLES ANGLES DRAFT UNITS IN [mm] 1° 1-1/2° ALL DIMENSIONS APPLY AFTER PLATING

TITLE: SPEC. CONTROL DRAWING STEPPER DRIVEN VARIABLE TRANSFORMER MODEL SD1510

DRAWN BY S.A. SMITH DATE 12/7/95 FIRST USED ON DO NOT SCALE DWG. CUSTOMER APPROVAL DATE

CHECKER DATE WEIGHT APPROX. CODE IDENT. NO. 83008 DWG. NO. 095-1804

ENGINEER DATE SCALE 1=1 SHEET 1 OF 1

STACO ENERGY PRODUCTS CO. A COMPONENTS CORPORATION OF AMERICA COMPANY DAYTON, OHIO U.S.A.